

|  | DB00 654 BB9<br>27 Longlands Rd, Manche<br>www.brbcGroup   Infoga | BC GROUP                           |                                    | DATE: 18 FEB                                       |   |  |
|--|---|------------------------------------|------------------------------------|--|---|--|
|  | Managers Name:<br>MICHAEL LLOYD                                   | CT AGREEM                          | ]                                  | Ext No<br>2 4 8 6 5 8 5                            |   |  |
| ANTERNA  | WORCHESTER   Identification number   4 8 9 6 5 2 3 1              | 4 7 8 5 2 6 3 1 8 4<br>INFORMATION |                                    | Post code<br>W 0 1 C H 2<br>imber<br>4 5 6 3 2 5 2 |   |  |
| THE REAL PROPERTY AND A DECEMBER OF A DECEMB | Name:   | SHAWN HOWARTH                      | /AY                                | _  | 5 |  |
|  | City  |                                    | Postcode                           | WO2CH4   |   |  |
|  | Contact Number<br>Gender  |                                    | Emergency Contac<br>Marital Status | • 07854096582                                      |   |  |
|  |   |                                    |                                    | · · · · ·  |   |  |

# Compact, Portable Document Scanner

ADS-1300



www.brother.eu

# Compact, Portable Document Scanner

Make everyday document scanning simple with the ADS-1300 compact, portable document scanner.

Scan and save your paper documents wherever you are working. Whether its utility bill, business documents or medical forms, once plugged into your laptop, you can scan and securely store data digitally and have instant access whenever you need it.

ADS-1300

# Key features:

- Scan up to 30ppm
- 60ipm, 2-sided colour scan
- 20 Sheet Automatic Document Feeder (ADF)
- Power directly via USB Type-C
- Control up to 3 scan activity shortcuts direct from the device
- Dedicated plastic ID card slot
- Scan to PC<sup>3</sup>, Cloud<sup>3,</sup>, USB Host
- PDF editing software included
- Optional paper output tray available

Scanning on the move

Designed with flexibility in mind, easily scan and save your paper documents whilst you are out of the office. Once plugged into your laptop, you can use the ADS-1300 to scan documents when it is most convenient for you.

High performance, every time

No matter where you scan from, you will get the same high performance, every time. With scan speeds of up to 60 sides per minute (2-sided), documents are saved quickly and effortlessly to PDF, File, Email and USB Host.


# Versatile media handling

The time-saving 20 sheet Automatic Document Feeder (ADF) manages various sizes and thicknesses of paper (up to 128gsm) with ease. Whilst the dedicated card slot comfortably handles plastic ID cards.

# Industry-leading software

Available as standard, Power PDF provides you with the flexibility to easily convert, edit and share documents in seconds.

Together with Kofax PaperPort, a document management solution, workflows can be created so that you can share, search and organise documents with ease and accuracy.



#### Product Form Factor Sheet Fed Portable Desktop Document Scanner Technology

Dual CIS

(contact Image

Sensor), LED Array Light Source Control Panel LED, Keys

Backup Clock Up to 24 hours

# Local Interface

USB Type-C 3.2 Gen1, USB 2.0 Host (Rear) Up to 128GB **Configurable Shortcuts** 3

### Scan

Scan Speed (A4) Colour and Mono (300dpi) Up to 30ppm (pages per minute) (USB bus powered)<sup>10</sup> Scan Speed 2-Sided (A4) Colour and Mono (300dpi) Up to 60ipm (images per minute) (30 sheets per minute) (USB bus powered)<sup>10</sup> Resolution Optical

Up to 600 x 600dpi (dots per inch)

Interpolated<sup>3</sup> Up to 1,200 x 1,200dpi (dots per inch)

Wake-up Time USB 1.0sec

### Colour Depth

48 bit colour processing (Input) 24 bit colour processing (Output)

## **Grey Scale**

256 levels (8 bit)

Scanner Functions

## **Machine Functions**

File Format Support Including (Standard)PDF, PDF/A-1b), JPEG, TIFF Direct Scan Yes<sup>9</sup>

#### Destinations<sup>3</sup>

Scan to PC (Image), Workflow, SharePoint (On Premise), Cloud

#### Feed Control

ADF Automatic Pop Up Edge Guide, Card Slot (Portrait) Separation Switch, Resume Scan<sup>3</sup>

#### **Configurable Shortcuts**

Create up to 3 preset scan to profiles using Brother iPrint&Scan for Desktop

#### Image Processing<sup>3</sup> Advanced Features

Auto Deskew(Feed)9, Detect End of Page<sup>5</sup>, Margin Setting<sup>5</sup>, Auto Image Rotation<sup>5</sup>, Edge Fill<sup>5</sup>, Tear Fill<sup>5</sup>, Punch Hole Removal<sup>5</sup>, Auto Colour Detect Adjust<sup>9</sup>, Blank Page Removal<sup>9</sup>, Diffusion Adjustment - Grey, Colour Tone Adjustment, Background Processing<sup>5</sup>, Colour Drop<sup>5</sup>, Edge Emphasis⁵, Moire Reduction<sup>5</sup>, Vertical Streak Reduction<sup>5</sup>, B&W Threshold Adjustment<sup>5</sup>, Character Correction, B&W Inversion, Noise Reduction, Remove Ruled Line, 2in1 Scan, 1to2 Scan, Carrier Sheet Mode, Plastic Card Mode, Single Page Scan<sup>5</sup>, Continuous Scan<sup>5</sup>, Barcode Detection<sup>5</sup>, JPEG Compression<sup>5</sup>, Digital Imprinter<sup>5</sup>, Custom TWAIN **Profiles**<sup>5</sup>

| Software <sup>2</sup> | Windows<br>Drivers<br>TWAIN  <br>WIA<br>Windows® 10, 11<br>Software for Windows<br>Brother iPrint&Scan for<br>Desktop, Kofax PaperPort<br>14SE with OCR, Kofax Power<br>PDF Standard v5, Remote<br>Setup<br>Visit support.brother.com for a full<br>to download the latest drivers and   |  |
|-----------------------|--|--|
| Media Handling        | Media Input / Output<br>ADF<br>Up to 20 sheets <sup>4</sup><br>Media Sizes<br>Multiple Pages <sup>8</sup><br>Width 51 - 215.9mm,<br>Height 70 - 355.6mm<br>Media Type<br>ADF<br>Plain Paper, Thin Paper,<br>Thick Paper, Thin Paper,<br>Thick Paper, Thicker Paper,<br>Recycled Paper, Non carbon<br>paper,Receipt, Business<br>Card, Plastic Card | Media Weights and<br>Thickness<br>ADF<br>51.8 - 128 gsm<br>Paper 0.08 ~ 0.14mm<br>Long Paper<br>5000mm<br>(300dpi 1-sided single<br>paper) |
| Security Features     | <b>Kensington Lock</b><br>Yes  | Interface Lock<br>USB Host   |
| Consumables           | Carton Contents  | Optional A3 Carrier Sheet  |

Consuma and Accessories

ADS machine, USB Type-C Cable, Quick setup guide, Product safety guide, Warranty Replacement **Separation Pad** SP-2001C 10,000 sheet

**Replacement Pickup** Roller PUR-2001C 100,000 sheet CS-A3301 500 times (Pack of 2) **Optional Output Tray** OT-1001C

**Optional Legacy Kit** 

AC Adapter with barrel

connector, USB Cable

(Type-C - Type-A): LK-1001CUK, LK-

1001CEU

**Optional USB-C Power** Adapter USB Type-C AC Power Adapter: PA-AD-004UK, PA-AD-004EU

Firmware Updates 2,8

Linux

**Drivers** SANE

your PC

Card Slot 1 Plastic Card (Portrait) Without Emboss (0.76-1.02mm)

Mediar Plasti24Cand) Size Width (ISO) - 53.98mm (Min/Max 51-55mm), Length (ISO) - 85.60mm (Min/Max 80.825-90.375mm)

or

Yes

Easy Setup<sup>12</sup> Simplifying the install process with easy access to the right drivers and software for the installation of your Brother machine for

# Dimensions and Weights

With Carton Dimension 369 (W) x 158 (D) x 200 (H) mm Weight 1.70 kg

#### Without Carton

Dimension Input Tray Closed 288(W) x 101(D) x 85(H) mm Input Tray Extended 288(W) x 211(D) x 205(H) mm Weight 1.37kg

### Environment

**Power Requirements** AC:100-240V, 50/60 Hz, DC: 5V, 3A USB: DC5V, 3A(Type-C)

**Power Consumption** (Scanning) AC:~11 W, DC:~9 W (Ready) AC:~5 W, DC:~4 W (Sleep) AC:~1.3 W, DC:~1 W (Off) ~0.1W

**Power Saving Mode** This enables the scanner to consume less energy when not in use Sound Power Level (Scanning) 62dB

**Operating Environment** 

Storage Environment

Humidity 20 - 80 %

Humidity 10 - 90 % 0°C - 40°C

5°C - 35°C

41°F - 95°F

32°F - 104°F

**RoHS** Yes

**GS Mark (Germany)** Yes

1 Maximum number of scanned pages per month can be used to compare design durability between like Brother products. For maximum scanner life, it is best to choose a scanner with a duty cycle that far exceeds your scan requirements

- 2 Download from the Brother Solutions Centre <u>http://solutions.brother.com</u>
- 3 All supported using downloadable software
- 4 Capacity varies dependent on paper weight.
- 5 Windows Only
- 6 Windows & macOS
- 7 Windows server support scanner driver
- 8 Document sizes larger than A4, but not exceeding A3, can be scanned (single-side) using carrier sheet
- 9 300dpi only
- 10 Requires USB Type-C connection with 15W power source (not included)
- 11 For more information visit https://setup.brother.com





#### Working with you for a better environment

At Brother, our green initiative is simple. We strive to take responsibility, act respectfully and try to make a positive difference to help build a society where sustainable development can be achieved. We call this approach Brother Earth. www.brotherearth.com All specifications correct at the time of printing and are subject to change. Brother is a registered trademark of Brother Industries Ltd. Brand product names are registered trademarks or trademarks of their respective companies.

